Earthing



Common Point Grounding Units Installation Instructions



Description

Per ANSI/ESD S20.20, all conductors, including personnel, must be electrically connected and attached to a known ground. EOS/ESD S6.1 recommends hard ground, without resistor, of worksurface or floor mats. Per ANSI/ESD S20.20, ground fault circuit interrupters (GFCI) should be considered to provide personnel protection.

Desco offers a number of common point grounds and wrist strap ground connectors designed to ground multiple operators oritems.



Figure 1. 09740/09741 wrist strap bench ground.

The 09740/09741 wrist strap bench ground is a wrist strap ground connector and consists of a mounting bracket with two standard banana jacks installed and soldered to a ten foot ground wire terminated with a ring terminal with 0.200° hole.

The 09741 includes a wrist strap parking station. See figure 2.



Figure 2. 09741 premium bench mounted ground with parking station

The 09837 Multi Grounding Hub is designed for use as either awriststrap ground connector or as a common point ground for all items to be grounded at a bench (i.e. table mat ground cord, floor mat ground cord, banana jack ground block, etc.). The Multi Grounding Hub incorporates six standard banana jacks, and sixterminations forring terminals (10-32 screw in threaded holes).





Figure 4. 09835/09836 quad common point ground

The 09835/09836 quad common point ground is designed for us eas either a wrist strap ground connector or as a common point ground. The quad ground incorporates four standard banana jacks, a 10mm snap stud, and ten feet of ground wire terminated with a ring terminal with a 0.200"I.D. hole. The model 09836 also incorporates a 1 megohm resistor in series with the snap stud.



Figure 5. 09820/09821/09825/09826 common point ground.

The 09820/09821/09825/09826 common point ground is designed to ground bench mats by snapping on the mat's stud, and to provide a convenient wrist strap ground connector. Items09820/09821 incorporatetwo standard banana jacks, a 10mm snap socket, and 10 feet of wire terminated with a ring terminal with a 0.200° I.D. hole. Items 09825/09826 have a 10mm snap stud and 15 feet of wire. Items 09821/09826 also incorporate a one megohm resistor in series with the snap.



Figure 6. All elements at the ESD work station should be connected to the same common point ground, such as 09837 Multi Grounding Hub.

The 09740/09741, 09835/09836 and 09820/09821/09825/09826 are shipped with an extra ring terminal so that the ground wire may be cut to length during installation. The 09740/09741 and 09835/09836 feature a pair of mounting holes designed to accommodate standard#10 screws, allowing the units to be mounted to the work bench.

DE8CO WE8T - 3651 Walnut Avenue, Chino, CA 91710 * (909) 627-8178 DE8CO EA8T - One Colgate Way, Canton, MA 02021-1407 * (781) 821-8370 * Website: Desco.com

TB-2003 Page 1 of 3 March 2015

Baskiville.com Ltd. Tel: 0508 227548 © 2015 DESCO INDUSTRIES, INC. Employee Owned

Email:orders@baskiville.com



Proper Grounding

Wrist straps, work surfaces, floor mats and other electrostatic discharge (ESD) protective products should be grounded to a common point ground.

COMMON POINT GROUND

Per ANSI/EOS/ESD S6.1, Grounding paragraph 4.1.1 "Every element to be grounded at an ESD protected station shall be connected to the same common point ground."

ESD Handbook TR 20.20 paragraph 5.1.3 Basic Grounding Requirements "The first step in ensuring that everything in an EPA is at the same electrical potential is to ground all conductive components of the work area (worksurfaces, people, equipment, etc.) to the same electrical ground point. This point is called the common point ground. The next step in completing the ground circuit is to connect the common point ground to the equipment ground (third wire, green).

If all elements are connected to the common point ground, even if the equipment ground connection is compromised, all workstation elements will be connected and be at equipotential or at the same charge. Being at the same electrostaticcharge will mean that no discharge should occur.

Connect the ground wire directly to the nearest utility" green wire" ground point. In a properly wired building, the "green wire" equipment groundpoint may be the centers crewof the standard 110VAC outlet. Some special outlets may "float" the center screw. Test before you hook up.



Figure 7. Recommended grounding point.

Individual work stations must be individually grounded to the "green wire" equipment ground. For ESD worksurface installation information, see Desco Technical Bulletin TB-2000

Always Test the Ground Before You Use It and Periodically Thereafter

You should not assume that any electrical outlet is properly wired. Even if it was originally wired correctly, it can become ungrounded due to corrosion and wear. Test the equipment ground you intendto use before you hook up. Use Desco 98132 AC Outlet & Wrist Strap Tester to verify proper wiring of the electrical outlet (equiment ground).

Installation

After you have selected and tested your grounding point, you will need to determine the method of installation for the type of grounding block that you have selected. Installation of common point units as grounding blocks is outlined below. Installation of the 09835/09836 and 09820/09821/09825/09826 as common point ground cords for a work surfaces is also discussed below.

WRIST STRAP GROUND CONNECTORS

- Select the most convenient location on the work bench for grounding of wrist straps and other grounding devices.
- 2. Position the 09740/09741 or 09835/09836 and use the two#10 mounting holes to secure to the work bench.
- Bring the wire neatly backtoy our grounding point. You may wish to use wire brack ets to hold the wire in place and out of the way. Cut and strip the end of the wire to properly fit your ground point. Install and crimp the extra ring terminal provided.



Figure 8. Installation of grounding blocks.

To check resistance, use an ohmmeter from the banana jacks to the common ground point. It should readless than 1 Ohm AC impedance for items 09740/09741,09820/09825 and 09835 and 1 megohm (10° ohms) for items 09836 and 09821/09826.

GROUNDING POINT

As previously mentioned, the 09835/09836 and the 09820/09821/09825/09826 can be installed as a wrist strap ground connector for ESD protective work surfaces.

 Position or lay the works urface in the desired location Snap the ground to it. These units connect with a 10mm socket snap.



FB-2003 Page 2 of 3

IDUSTRIC¹

Email:orders@baskiville.com

Earthing



- Bring the other end of the ground cord to a verified groundingpoint and attachit using the ring terminal. Tie the ground wire to the bench to keep it neatly out of the way. You may cut and strip the ground wire to a shorter length and attach it using the extra ring terminal included with each ground cord.
- After installation, the work surface along with the banana jacks are all electrically connected to ground. The banana jacks will now serve as wrist strap ground connectors.
- To check resistance, use an ohmmeterfrom the ground point snap on the mat to the common ground point. It should read 1 megohm ±20 percent if you are using a model 09836, 09821, or 09826 ground cord, and less than 1 Ohm AC impedance if you are using a 09835, 09820, or 09825 non-resistor ground cord.

MULTI GROUNDING HUB

The 09837 Multi Grounding Hub can be mounted either on a bench legortabletop.



Figure 10. Installation of multi grounding hub.

Maintenance

You should set up a an auditing schedule to be sure that all ESD grounds are inspected and tested per your compliance verification plan required by ANSI/ESD S20.20. Some companies test once every six months.

> DE8CO WE8T - 3651 Walnut Avenue, Chino, CA 91710 • (909) 627-8178 DE8CO EA8T - One Colgate Way, Canton, MA 02021-1407 • (781) 821-8370 • Website: Desco.com

TB-2003 Page 3 of 3

Baskiville.com Ltd. Tel: 0508 227548 Limited Warranty, Warranty Exclusions, Limit of Liability and RMA Request Instructions See Desco Terms and Conditions

Email:orders@baskiville.com

0 2015 DESCO